

Application No. 10/809,697  
Reply to Office Action mailed on June 9, 2006

### **Amendments to the Claims**

The listing of claims will replace all prior versions and listings of claims in the application:

### **Listing of Claims:**

1. (currently amended) A computing device comprising:
  - a clock circuit for generating a first clock signal, ~~[[and]]~~ a second clock signal, and  
a third clock signal;
  - a first sub functional block (SFB) having an input port for receiving the first clock  
signal;
  - a second sub functional block (SFB) having an input port for receiving the first  
clock signal;
  - a first functional circuit block (FCB) including the first SFB and for operating in  
accordance with predetermined parameters, the first FCB having a clock control port for  
providing a copy of the first clock control signal, ~~[[and]]~~ a first clock signal input port for  
receiving a switchably coupled second clock signal, a first FCB control input port and a  
first FCB control output port, the first FCB having a circuitry portion for operating in one  
of a normal mode of operation and in a reduced power consumption mode of operation in  
dependence upon the switchably coupled second clock signal;
  - a second functional circuit block (FCB) including the second SFB and for operating  
in accordance with predetermined parameters, the second FCB having a second clock  
control port for providing a second clock control signal, ~~[[and]]~~ a second clock signal input  
port for receiving a switchably coupled third clock signal, a second FCB control input port  
and a second FCB control output, the second FCB having a circuitry portion for operating  
in one of a normal mode of operation and in a reduced power consumption mode of  
operation in dependence upon the switchably coupled third clock signal; ~~[[and]]~~
  - a first clock control circuit for receiving the second clock signal and for switchably  
coupling the second clock signal to the first clock signal input port in dependence upon the  
first clock control signal; and wherein

Application No. 10/809,697

Reply to Office Action mailed on June 9, 2006

a master-slave relationship is established by at least one of the first FCB control output port being coupled to the second FCB control input port for receiving a FCB control signal from the first FCB for enabling and disabling of the second FCB circuitry portion and the second FCB control output port being coupled to the first FCB control input port for receiving a FCB control signal from the second FCB for enabling and disabling of the first FCB circuitry portion.

2. (cancelled)

3. (currently amended) A computing device according to claim 1 [[2]], comprising a second clock control circuit for receiving the third clock signal and for switchably coupling the third clock signal to the second clock signal input port in dependence upon the second clock control signal.

4. (cancelled)

5. (cancelled)

6. (original) A computing device according to claim 1, wherein a plurality of power consumption modes of operation for the first FCB are achievable between the normal mode of operation and the reduced power consumption mode of operation.

7. (currently amended) A computing device according to claim 1 [[2]], wherein a plurality of power consumption modes of operation for the second FCB are achievable between normal mode of operation and the reduced power consumption mode of operation.

8. (original) A computing device according to claim 1, comprising a frequency multiplier and divider circuit coupled with the clock circuit for receiving of at least one of the first clock signal and the second clock signal for varying a frequency of at least one of the first clock signal and the second clock signal.

Application No. 10/809,697  
Reply to Office Action mailed on June 9, 2006

9. (original) A computing device according to claim 1, comprising a frequency multiplier and divider circuit coupled with the first functional circuit block (FCB) the clock circuit for decreasing a frequency of the first clock signal when the first FCB is for operating in the reduced power consumption mode of operation.

10. (cancelled)

11. (currently amended) A method of controlling power consumption:  
providing a first FCB for processing data using a first clock signal provided by a first clock circuit;  
providing a second FCB for processing data using a second clock signal provided by a second clock circuit;  
receiving a FCB control signal by the first FCB and the second FCB;  
determining whether the FCB control signal is for operating of at least one of the first FCB and the second FCB in one of a normal mode of operation and a reduced power consumption mode of operation; ~~[[and;]]~~  
performing one of enabling of at least one of the first clock circuit and the ~~[[a]]~~ second clock circuit in dependence upon whether at least one of the first FCB and the second FCB are for operating in the normal mode of operation and varying a frequency of at least one of the first clock circuit and the ~~[[a]]~~ second clock circuit in dependence upon whether at least one of the first FCB and the second FCB are for operating in the normal mode of operation; and  
providing at least one of the first FCB control output port being coupled to the second FCB control input port for receiving a FCB control signal from the first FCB for enabling and disabling of the second FCB circuitry portion and the second FCB control output port being coupled to the first FCB control input port for receiving a FCB control signal from the second FCB for enabling and disabling of the first FCB circuitry portion.

12. (original) A method according to claim 11, wherein determining comprises determining whether at least one of the first FCB and the second FCB are selected for processing of data.

Application No. 10/809,697

Reply to Office Action mailed on June 9, 2006

13. (original) A method according to claim 11, wherein operating in the reduced power consumption mode of operation comprises disabling a majority of internal circuitry within at least one of the first FCB and the second FCB.

14. (cancelled)

15. (currently amended) A method according to claim 12 ~~[[14]]~~, wherein the first FCB control signal is for varying a frequency of the second clock signal for the second FCB.

16. (currently amended) A method according to claim 12 ~~[[14]]~~, comprising increasing a frequency of the first clock signal where the first FCB is for operating in the normal power consumption mode of operation.

17. (original) A method according to claim 11, comprising decreasing a frequency of the second clock signal when the second FCB is for operating in the reduced power consumption mode of operation.

18. (original) A method according to claim 17, comprising increasing a frequency of the second clock signal when the second FCB is for operating in the normal power consumption mode of operation.

19. (currently amended) A method comprising:

providing a first functional circuit block (FCB) for processing of data using a first clock circuit;

providing a second FCB for processing of data using a second clock circuit;

~~[[and,]]~~

switchably enabling and disabling the first and second clock circuits independently in dependence upon performance requirements of the first and second FCBs~~[[:-]]~~; and

establishing a master-slave relationship by at least one of coupling a first FCB control output port to a second FCB control input port for receiving a FCB control signal

Application No. 10/809,697  
Reply to Office Action mailed on June 9, 2006

from the first FCB for enabling and disabling of the second FCB circuitry portion and coupling a second FCB control output port to a first FCB control input port for receiving a FCB control signal from the second FCB for enabling and disabling of the first FCB circuitry portion.

20. (original) A method according to claim 19, comprising determining whether at least one of the first FCB and the second FCB are for processing of data, where at least one of the first and second clock circuits are disabled when the at least one of the first FCB and the second FCB are other than for processing of data.

21. (currently amended) A computer readable storage medium comprising:  
first instruction data for providing a first functional circuit block (FCB) for processing of data using a first clock circuit;  
second instruction data for providing a second FCB for processing of data using a second clock circuit; and,  
third instruction data for switchably enabling and disabling the first and second clock circuits independently in dependence upon performance requirements of the first and second FCBs.

22. (currently amended) A computer readable storage medium comprising instruction data stored thereon, the instruction data comprising:  
first instruction data for providing a first FCB for processing data using a first clock signal provided by a first clock circuit;  
second instruction data for providing a second FCB for processing data using a second clock signal provided by a second clock circuit;  
third instruction data for receiving a FCB control signal by the first FCB and the second FCB;  
fourth instruction data for determining whether the FCB control signal is for operating of at least one of the first FCB and the second FCB in one of a normal mode of operation and a reduced power consumption mode of operation; and,

Application No. 10/809,697  
Reply to Office Action mailed on June 9, 2006

fifth instruction data for performing one of enabling of at least one of the first clock circuit and a second clock circuit in dependence upon whether at least one of the first FCB and the second FCB are for operating in the normal mode of operation and varying a frequency of at least one of the first clock circuit and a second clock circuit in dependence upon whether at least one of the first FCB and the second FCB are for operating in the normal mode of operation.